



KODAK Power Station

S300



Model	S300
Built-in Battery	LMFP
Battery Capacity	236.25Wh /63000mAh
DC Output	12V DC Output *2 /10A, Cigarette lighter*1
USB Output	QC3.0 Output *1 ,5V 2.4A,PD65W bidirectional
AC Output	2* 110V/230V~50/60Hz 300W (Peak 600W) pure sine wave
DC Input	16V 4A
MPPT Input	180W
Charging Time	2.5 H
LED light	6W LED light,Red/white warning light



238X196X218mm
3,9Kg



291x241x268mm
5,30Kg



0 54 19980 44113 3

3000mAh	25W	40W	60W	65W	110W
18,2 Hrs	8,1 Hrs	5Hrs	3,4Hrs	3,2Hrs	4,2Hrs

